

Postle Industries, Inc.

Cleveland, OH USA

Phone: 216-265-9000

Fax: 216-265-9030

E-Mail: sparky@postle.com

Web Site: www.hardbandingsolutions.com



Hardbanding Wire

Data Sheet

POSTALLOY[®] DURABAND[®] NC

Description

Postalloy[®] DURABAND[®] NC is a 100% crack-free hardband that provides maximum protection of the tool joint and casing.

DURABAND[®] NC microstructure consists of a hard, but tough tool steel matrix with a high volume of tightly packed micro-constituents. This combination ensures excellent wear resistance in open hole drilling as well as being *CASING FRIENDLY*. Typical hardness values of 57-60Rc can be expected when applied to new tools or properly rebuilt joints. Deposits are smooth and free of any slag. DURABAND[®] NC can be applied over itself and over TUFFBAND[®] NC without removal, but only if the surface has been properly cleaned and inspected. DURABAND[®] NC can be applied over some competitive products without removal. Please contact our Engineering Department for complete procedures.



Welding Parameters

Diameter	1/16" (1.6mm)
Polarity	Electrode Positive
Gas	98% Argon/2% Oxygen
Gas Flow	32 - 37 CFH (Typical 35 CFH)
Current <i>amps</i>	300-365 (Typical 320A)
Voltage <i>volts</i>	29-33 (Typical 30V)
Stickout <i>inch (mm)</i>	3/4"-1-1/4" (19-32mm) (Typical 1" or 25mm)
Preheat	350/450°F (165/232°C)
Maximum Interpass	800 °F (427°C)
Post Welding	Slow Cool to Room Temp

Packaging 50 Lb. Spools Standard

Other packaging available upon request



Duraband[®] NC Hardbanding
Uses: New Application and
Re-Application to Tool Joints

Power sources often operate differently even with the same consumable weld wire. If switching from a rectifier (inverter), which is often found in stationary units, to a motor generator, which is often found on mobile units, a slight adjustment in welding parameters may be necessary. This is also true when switching from a motor generator to a rectifier (inverter). Usually a slight change in wire feed (amperage), voltage and electrical stickout will be enough to arrive at acceptable settings.